


### Male Line Socapex Power & Control Connector

Cable guage/size:

U, D, C, & E for Control - 1 mm<sup>2</sup> - Any colours

L1, L2, L3 & E for Power - 1.5mm<sup>2</sup> **Colours as shown above**

Solder a tinned wire bridge as shown  between pins 7&16(for L1), 9&17 (for L2), and 11&18 (for L3).

Solder three parallel sets of L1, L2, and L3 cables from these wire bridges to the three separate Red C-Form Ch 1, 2, and 3 connectors

### LV6/LV12 Ceep/Socapex splitter wiring